



3. If you connected the smart hub via Wi-Fi, connect your mobile device to the following Wi-Fi network:
- network name: "**Niko**" followed by the last 4 characters of the smart hub's MAC address (XX:XX).
 - password: serial number of the smart hub (SN: XXXXXXXXXXX).
- Result: On mobile devices, the smart hub's web portal opens automatically.



4. To set the smart hub's network connection, proceed as follows:
- Open a web browser and go to the address: **Nikoxxx.local** (xxxx = the last 4 characters of the smart hub's MAC address (XX:XX)).

On a mobile device, the smart hub's web portal is already open.

- Enter the password. The password is the smart hub's serial number (SN:XXXXXXXXXX).
Result: An overview of all available wireless networks is shown.
- Select your preferred network for the smart hub. (if applicable) Enter the password for this network.
Result: The smart hub connects to your own wireless network. The smart hub stops broadcasting its own Wi-Fi network.

To make changes to the Wi-Fi configuration of the smart hub, restart the smart hub by cutting the power supply for a couple of minutes. The smart hub will then transmit its own Wi-Fi network again for 5 minutes.